

Product data sheet

Specifications

SQUARE D



Surge protection device, Surgelogic, 160kA, 600 VAC delta, 3 phase, 3 wire, NEMA 4X

SSP09EMA16S

● Discontinued on: 21 September 2020

● End-of-service on: 21 September 2020

● Discontinued

SSP09EMA16S has not been replaced. Please contact your customer care center for more information.

Product availability : Non-Stock - Not normally stocked in distribution facility

Price* : 5,999.70 USD

Main

Product Surge protection device

Range Surgelogic

Device Short Name EMA

Complementary

Surge Current 160 kA

Voltage Rating 600 V delta AC

Number of Phases 3 phase

Wiring Configuration 3-wire

Connection Lugs AWG 10...AWG 2 copper 35.40 lbf.in (4 N.m)

MCOV 840 V

Nominal Discharge Current 10 kA

SCCR 200 kA

Local Signalling Status LED green per phase normal operation
Status LED red per phase fault

Provided Equipment Alarm enable/disable switch
Surge counter
Dry contacts

Device Mounting Surface

Height 22.67 in (575.8 mm)

Width 11.70 in (297.2 mm)

Depth 9.40 in (238.8 mm)

Cable length 19.02 in (483 mm)

Environment

Enclosure Rating NEMA 4X

* Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Enclosure Material	Stainless Steel
Standards	CSA C22.2 No 8 UL 1449:ed. 4 UL 1283:ed. 5
Ambient Operating	149 °F (65 °C)

Ordering and shipping details

Category	08464 - SURGE PROTECTION EMA
Discount Schedule	DE1B
Nbr. of units in pkg.	1
Package weight(Lbs)	32.2 lb(US) (14.61 kg)
Returnability	No
Country of origin	MX

Offer Sustainability

California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov
EU RoHS Directive	Compliant EU RoHS Declaration
Mercury free	Yes
RoHS exemption information	Yes
China RoHS Regulation	China RoHS declaration Product out of China RoHS scope. Substance declaration for your information.