



## 120V INCANDESCENT SINGLE POLE VACANCY SENSOR, MANUAL OPERATION, WHITE

RW500BWCC4 | [Pass & Seymour](#)

### FEATURES & BENEFITS

Designed to replace a standard light or fan single pole switch, this vacancy sensor controls most types of lighting and is ideal for bedrooms and baths.



### LEED CONTRIBUTION

- California Title 24 compliant.
- Lighted switch for visibility in darkened rooms.
- Manual-ON operation.
- Fixed 30-minute time delay, no adjustment necessary.
- Low-profile styling with uniform color-matched lens and device.
- Coverage: 180 degrees, max. 600 ft.2 (56m2).
- Load: Incandescent.
- For covering patents, see [www.legrand.us/patents](http://www.legrand.us/patents).

### SPECIFICATIONS

#### GENERAL INFO

Color: White

Number Of Poles: 1

Number Of Wires: 2

#### LISTING AGENCIES/THIRD PARTY CERTIFICATIONS

RoHS: Yes

cULus: Yes

UN SPSC: 39121502

#### DIMENSIONS

Depth (US): 1.88"

Height (US): 2.63"

Width (US): 1.69"

#### TECHNICAL INFORMATION

Volts (AC): 120VAC, 60Hz

Watts: 25-500W Incandescent

#### BUY AMERICAN ACT COMPLIANCE

Country Of Origin: CHINA

Buy American Act Status: No