

Eaton FH42

Catalog Number: FH42

Eaton A200/B100 heater, Used with Starter Sizes 0,1, and 2, A200/B100 Heater, NEMA, Ambient 10.4-11.3, 12.0-13.1A, Non-Comp 9.6-10.5, 11.8-12.7A, Used with Starter Sizes 0,1, and 2, Type A and B, Thermal and Fast Trip

General specifications



Product Name	Catalog Number
Eaton A200/B100 heater	FH42
UPC	Product Length/Depth
786678670126	2.1 in
Product Height	Product Width
0.8 in	1.4 in
Product Weight	Warranty
0.04 lb	Eaton Selling Policy 25-000, one (1) year from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first.
Certifications	Catalog Notes
UL Listed	Select heater coils based on full load current(FLA) shown on motor nameplate.
CSA Certified	Heater coils are rated to protect 40 degree C rise and a service factor of 1.15, Single-Phase requires 2 heaters, Three-Phase Requires 3 heaters.

Product specifications

Design

NEMA

Full load current range

Ambient 10.4-11.3, 12.0-13.1 A, Non-Comp 9.6-10.5, 11.8-12.7 A

Overload relay

Type A and B

Special features

Used with Starter Sizes 0,1, and 2

Type

A200/B100 Heater

Used with

Used with Starter Sizes 0,1, and 2

Trip type

Thermal and fast trip

Resources

Catalogs

Eaton's Volume 5—Motor Control and Protection

Installation instructions

Instructions for A200, A210, A250 size 6, two- or three-pole non-reversing or reversing motor controllers

Specifications and datasheets

Eaton Specification Sheet - FH42