

# Product data sheet

Specifications



Complete control station, Harmony 9001K, 10A, zinc, grey, 3 push buttons 3NO + 3NC OPEN CLOSE STOP, NEMA 3 4 13

9001KYK33

## Main

Range of product	Harmony 9001K
Product or component type	Complete control station
Device short name	KY 9001KY
Provided equipment	Contact block Legend plate
Contact block name	KA1

## Complementary

Enclosure/cubicle description	Surface mounting
Enclosure material	Die cast zinc alloy, colour: grey
Type of installation	Indoor/outdoor
Control station composition	3 push-buttons with 3 NO + 3 NC contacts OPEN-CLOSE-STOP
Connections - terminals	Screw-clamp terminals
[Ie] rated operational current AC	10 A

## Environment

NEMA degree of protection	NEMA 3/4/13
---------------------------	-------------

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	12.192 cm
Package 1 Width	13.462 cm
Package 1 Length	29.464 cm
Package 1 Weight	2.018 kg



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

Total lifecycle Carbon footprint **16**

Environmental Disclosure [Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard Yes

Packaging without single use plastic Yes

[EU RoHS Directive](#) Pro-active compliance (Product out of EU RoHS legal scope)

California proposition 65 **WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to [www.P65Warnings.ca.gov](#)**

## Use Again

### Repack and remanufacture

End of life manual availability [End of Life Information](#)

Take-back No