

Product data sheet

Specifications

SQUARE D



NEMA Motor Starter and contactor, Type S, hand/off/auto selector switch kit, NEMA 1

9999SC2

Product availability: Stock - Normally stocked in distribution facility

Main

| | |
|----------------|----------------------|
| Product Range | Type S |
| Component type | Selector switch |
| Used with | contactor starter |

Complementary

| | |
|-------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| NEMA size | 00 1 0 2 3 |
| Marking | HAND-OFF-AUTO |
| Mounting Mode | Panel-mounted |
| Rated breaking capacity | 3 A 120 V AC inductive control circuit UL 508 1.5 A 240 V AC inductive control circuit UL 508 0.6 A 600 V AC inductive control circuit UL 508 5 A 600 V AC resistive control circuit UL 508 |
| Height | 1.88 in (47.75 mm) |
| Width | 3.81 in (96.77 mm) |
| Depth | 5.63 in (143.002 mm) |
| Net Weight | 0.51 lb(US) (0.23 kg) |

Environment

| | |
|---------------------------|-----------------------------------|
| NEMA Degree of Protection | NEMA 1 |
| Product Certifications | UL Listed UL Recognized CSA |

Ordering and shipping details

| | |
|-------------------|--------------|
| Category | US10CP121761 |
| Discount Schedule | OCP1 |
| GTIN | 785901783008 |
| Returnability | Yes |
| Country of origin | MX |

Packing Units

| | |
|------------------------|-----|
| Unit Type of Package 1 | PCE |
|------------------------|-----|

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

| | |
|------------------------------|-------------------|
| Nbr. of units in pkg. | 1 |
| Package 1 Height | 2.008 in (5.1 cm) |
| Package 1 Width | 3.9 in (9.9 cm) |
| Package 1 Length | 5.9 in (15.0 cm) |
| Package weight(Lbs) | 6.7 oz (190.5 g) |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty | 18 months |
|-----------------|-----------|



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances

| | |
|----------------------------------------|----------------------------------------------------------------------------------------------------------------------|
| Packaging made with recycled cardboard | No |
| Packaging without single use plastic | No |
| EU RoHS Directive | Under investigation |
| California proposition 65 | WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov |

Use Again

Repack and remanufacture

| | |
|---------------------|------------------------------------------------------------------------------------------------------------------------------|
| Circularity Profile | No need of specific recycling operations |
| Take-back | No |
| WEEE Label | The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins. |