

3" x 2" Gangable Switch Boxes

3-1/2" Deep

Features


- Boxes – 3-1/2" deep
- Boxes – 18 cu in.
- Pre-assembled with 10-32 ground screw & 7-1/2" Long #12AWG solid pigtail
- Available in multiple KO sizes with adjustable plaster ears, brackets, NM Clamps, and MC Clamps where noted
- Gangable

Applications

- 3" x 2" Switch boxes can be installed in walls or ceilings for lighting fixtures, switches, receptacles or other outlet devices
- Switch boxes are used to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions
- The adjustable plaster ears allow for an easy "cut in" when switches or outlets need to be added


Standard Material

- Galvanized steel




SBG591

Eccentric KO
Does not include #12AWG
solid pigtail




SBG600

MC Clamp




SBG601

NM Clamp



SBG604

MC Clamp & FL bracket



SBG605

NM Clamp & FL bracket

All 3" x 2" gangable switch boxes are pre-assembled with 10-32 ground screw & 7 1/2" long #12AWG solid pigtail, with the exception of SBG591.

Catalog Number	UPC	Description	Knockouts			Cubic Inches	Ship Case	Weight/Case
			Sides	Ends	Bottom			
SBG591	00032	3-1/2" deep 1/2" Eccentric KO	(4) - 1/2"	(2) - 1/2", & (2) - 1/2" & 3/4" ECC	(2) - 1/2"	18	50	44
SBG600	00033	3-1/2" deep 1/2" KO with MC Clamp	(4) - 1/2"	(2) - 1/2" & 4 pryouts	(1) - 1/2"	18	50	48
SBG601	00039	3-1/2" deep 1/2" KO with NM Clamp	(4) - 1/2"	(2) - 1/2" & 4 pryouts	(1) - 1/2"	18	50	44
SBG604	00040	3-1/2" deep 1/2" KO with MC Clamp & FL bracket	(4) - 1/2"	(2) - 1/2" & 4 pryouts	(1) - 1/2"	18	20	18
SBG605	00044	3-1/2" deep 1/2" KO with NM Clamp & FL bracket	(4) - 1/2"	(2) - 1/2" & 4 pryouts	(1) - 1/2"	18	20	21