

Product data sheet

Specifications

SQUARE D



Panelboard accessory, NQ, deadfront kit, branch, 225A, 3 phase, 42 circuits

NQRPL442L2

Product availability: Stock - Normally stocked in distribution facility

Main

Product	Cover plate
Accessory / separate part category	Replacement part

Complementary

Number of spaces	42
Device Application	panelboard interior
Current Rating	225 A
Tightening torque	45...50 lbf.in (5.08...5.6 N.m) (AWG 6...AWG 2/0) 100 lbf.in (11.3 N.m) (AWG 6...AWG 2/0) 275 lbf.in (31.07 N.m) (AWG 6...350 kcmil) 275 lbf.in (31.07 N.m) (AWG 6...250 kcmil) 275 lbf.in (31.07 N.m) (AWG 4...300 kcmil)

Ordering and shipping details

Category	US1PE1A00014
Discount Schedule	PE1A
GTIN	785901677529
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.4 in (6.1 cm)
Package 1 Width	14.5 in (36.8 cm)
Package 1 Length	20.8 in (52.8 cm)
Package weight(Lbs)	6.0 lb(US) (2.7 kg)

Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Environmental Disclosure

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard **No**

Packaging without single use plastic **No**

[EU RoHS Directive](#) **Compliant**

California proposition 65

WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture

Circularity Profile **No need of specific recycling operations**

Take-back **No**