

# Eaton FH13

## Catalog Number: FH13

Eaton A200/B100 heater, Used with Starter Sizes 0,1, and 2, A200/B100 Heater, NEMA, Ambient .69-.75, .80-.87A, Non-Comp .64-.70, .78-.85A, Used with Starter Sizes 0,1, and 2, Type A and B, Thermal and Fast Trip

### General specifications



Product Name	Catalog Number
Eaton A200/B100 heater	FH13
UPC	Product Length/Depth
786678629261	2.1 in
Product Height	Product Width
0.8 in	1.3 in
Product Weight	Warranty
0.03 lb	Eaton Selling Policy 25-000, one (1) year from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first.
Certifications	Catalog Notes
UL Listed	Select heater coils based on full load current(FLA) shown on motor nameplate.
CSA Certified	Heater coils are rated to protect 40 degree C rise and a service factor of 1.15, Single-Phase requires 2 heaters, Three-Phase Requires 3 heaters

## Product specifications

### Design

NEMA

### Full load current range

Ambient 0.69-0.75, 0.80-0.87 A, Non-Comp 0.64-0.70, 0.78-0.85 A

### Overload relay

Type A and B

### Special features

Used with Starter Sizes 0,1, and 2

### Type

A200/B100 Heater

### Used with

Used with Starter Sizes 0,1, and 2

### Trip type

Thermal and fast trip

## Resources

### Catalogs

Eaton's Volume 5—Motor Control and Protection

### Installation instructions

Instructions for A200, A210, A250 size 6, two- or three-pole non-reversing or reversing motor controllers

### Specifications and datasheets

Eaton Specification Sheet - FH13



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com  
© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)